

Product designation

Receiver RFS 2

Article No. 36.134.00

Product description

Radio receiver with 99 studio addresses and 40 digitally coded frequency channels, which can be connected to broncolor units without a RFS 2 interface and to units of other brands (sync socket). In this way these units can be triggered by means of the transmitter RFS 2 (art. no. 36.133.00) from long distances. The receiver is provided with a set button and two other buttons to activate additional options. The radio receiver is supplied with a comprehensive set of cables, an AC adapter (USB) for battery-free operation and a base plate .

Scope of delivery

Receiver RFS 2 (including battery), bag, synchronous cable, Micro-USB cable, synchro-out cable broncolor, base plate, USB power supply device (including rechargeable batteries), instruction manual

Technical data

Number of studio addresses	99
Number of frequency channels	40
Operational distance outdoors	up to 200 m / 656 ft
Operational distance in closed rooms	up to 50 m / 164 ft
Dimensions (L x W x H)	68 x 38,5 x 25 mm / 2.7 x 1.5 x 1 inch
Weight	43 g / 35 oz
Trigger sequence per second	100
Power supply	3 V CR2450 lithium battery or from USB power supply device

Compatibility

This receiver allows to trigger broncolor units without an integrated receiver RFS 2 and also units of other brands. For flash triggering the transmitter RFS 2 (art. no. 36.133.00) will be needed.

Application

The receiver RFS 2 is an ideal tool for photographers who do not want to dispense with the latest radio technology. The receiver is the connecting link between the broncolor units without a RFS 2 interface and also units of other brands and the latest transmitter RFS 2.

Its enormous reception range is very advantageous for operation in large studios, on location and in studios with non-reflective walls. The receiver RFS 2 is powered by the USB power supply device provided. The illuminated LCD display shows all relevant settings at a glance.